

GLP Firmware Change Log

impression X5 (X5-19) / impression X5 Compact Firmware Log V1.0.1 / 03/24/2023



Below you will find the history of all fixture firmware versions since the release of the device. Please note the respective information on functional changes, extensions, optimizations, etc. Even if it is our goal to develop firmware updates without relevant performance changes, it can always happen that optimizations or bug fixes can affect the device performance. Please read the note on "INFO" as a matter of urgency.

We strongly advise that firmware updates be carried out on individual replacement devices first.

Likewise, updates should never be carried out shortly before an important use of the device. If in doubt, speak to your GLP Service Team.

- [23 Mar 2023 / Main changes from V0.14.5 to V1.0.1](#)
- [11 Jan 2023 / Main changes from V0.14.4 to V0.14.5](#)


23 Mar 2023 / Main changes from V0.14.5 to V1.0.1

VERSION DETAILS	<ul style="list-style-type: none">• Updated Color Calibration (4.5.0) (via iQ.Service App)• Added iQ.Gamut Color selection: Full, Rec.2020, Rec709, DCIP3.65• Added: Dimmer Curves Linear and S-Curve• Added and adjusted Fan Modes. Regulated Mode will be much more quite and turn off all fans when LEDs off and the temperature allows fans off.• Added: PWM Settings• Added: Hibernate : Caution, fixture needs wakeup via DMX or power-cycle to leave hibernate.• Added: Advanced Service Menu: Job Offsets (Pan, Tilt, Zoom)• Added: RDM : Set Factory Default Settings• Added: RDM : Get Fixture Serial Number
BUG FIXES	<ul style="list-style-type: none">• Fixed: Color Mixing: Previous Color Calibration version could lead to color and intensity jumps• Fixed: Increased Zoom Speed in Normal Performance Mode back to normal speed (faster).• Fixed: iQ.Mesh: Activate iQ.Mesh via DMX Control Channel, as long as the DMX Slot (012-013) is selected. When the slot is not selected anymore a 5 minute timeout starts after which the iQ.Mesh module will fall asleep.• Fixed: Update via iQ.Service App works fast as supposed to be. Unfortunately after this update ..• Changed: No Signal Mode: Default is now DMX-Hold

GLP Firmware Change Log

impression X5 (X5-19) / impression X5 Compact Firmware Log V1.0.1 / 03/24/2023



UPDATE PROCESS	<p>Fixtures need 4 updates. One after the other.</p> <p>Via D3Prog / RS485/ DMX</p> <ol style="list-style-type: none">1. Update the new Main Bootloader V1.0.0 via DMX/RS485 via D3Prog (impression-X5_1.0.0_BOOTDMX.bin)2. Update the new Main Application V 1.0.1 via DMX/RS485 via D3Prog (impression-X5_1.0.1_DMX.bin) <p>Change the Control Protocol in the Protocol Setup Menu to iQ.Mesh: Update via iQ.Service App:</p> <ol style="list-style-type: none">3. Update the iQ.Mesh Version to V5.0.314. Update the Color Calibration to V4.5.0 <p>If you have fixtures below version 0.14.5 or just an older set bootloaders: it could occur that after the BL update (step 1) the fixture needs about 5 minutes to prepare all internal updates with its display off. Please do allow the fixture these 5 minutes before proceeding with the main update step 2, while display is off still. The display will come back automatically during step 2.</p> <p>The first two updates can be done via DMX, D3Prog, daisy chain. When importing the bin files to a D3Prog make sure that you choose the file type „BIN“ before uploading the file to the programmer.</p> <div><p>Please make sure that no other DMX receivers or consoles are active on the line and fixtures Control Protocol is set to DMX for step 1 and step 2 and iQ.Mesh (iQ.Data) for step 3 and step 4. Do set to iQ.Mesh via Protocol setup menu, only! All fixture settings will perform a reset to factory defaults after the main application update (step 2), if updateing from 0.X.X to 1.X.X After step 4 remember to change back the Protocol Data In to DMX.</p></div>
INFO	<p> This update is show critical as pattern, dimming, colormix and shutter behavior is changed and should not be done on site.</p>
VERSION PACKAGE	<p>impression-X5_1.0.0_BOOTDMX.bin (provided via website/download) impression-X5_1.0.1_DMX.bin (provided via website/download) iQ.Mesh V5.0.31 (included in iQ.Service App) ColorCalibration V4.5.0 (included in iQ.Service App)</p>

11 Jan 2023 / **Main changes from V0.14.4 to V0.14.5**

VERSION DETAILS

• N/A

GLP Firmware Change Log

impression X5 (X5-19) / impression X5 Compact Firmware Log V1.0.1 / 03/24/2023



BUG FIXES	<ul style="list-style-type: none">• Fixed bug in dimmer curve in RGBL - ColorMix Mode
UPDATE PROCESS	<p>If fixtures are on V0.12.6 or earlier an iQ.Mesh Update has to be performed via the iQ.Mesh App. Afterwards 2 files have to be uploaded via DMX/RS485. First the new Bootloader, second, the Main application. Please take care that fixtures don't loose power between the two updates. (1, 2, 3) For the mesh update please refer to the separate mesh update manual.</p> <p>If fixtures are already on V0.14.4 only the main application V0.14.5 has to be uploaded. (3)</p> <p>1.) Mesh Update to Version 5.0.26</p> <p>2.) Upload: impression-X5_0.14.5_BOOTDMX.bin</p> <p>This has to be done via DMX, D3Prog, daisy chain. To get all drivers internally updated please wait 5 minutes after this update before you proceed with step 2. During Step1 the fixtures display can go off. Don't worry. Just wait the specified 5 minutes. The display will go On after step 2 again.</p> <p>3.) Upload: impression-X5_0.14.5_DMx.bin</p> <ul style="list-style-type: none">• When importing the bin files to a D3Prog make sure that you choose the file type „BIN“ before uploading the file to the programmer. <p>The fixtures can be updated daisy chain via DMX/RS485. Please make sure that no other DMX receivers or consoles are active on the line and fixtures Control Protocol is set to DMX</p>
INFO	<p>⚠ This update is show critical as pattern, dimming, colormix and shutter behavior is changed and should not be done on site. V0.12.4 and 0.12.6 is stable, still.</p>
VERSION PACKAGE	<p>impression-X5_0.14.5_DMx.bin impression-X5_0.14.5_BOOTDMX.bin</p>